

TECHNICAL NOTE

Date: May 2019

Ref: TN447

Raised by: RW

Distributed to: As Required



Soundtracs - Digico(UK) Ltd. Unit 10 Silverglade Business Park Chessington Surrey KT9 2QL England
Tel: +44 1372 845600 Fax: +44 1372 845656 email: support@digiconsoles.com

Upgrading SD5CS to V1090 Stealth Core 2

These instructions will guide you through updating your SD5CS Console from V1069 to the latest release. V1090 replaces V1069 as the latest release.

SD5CS V1090 is only compatible with External Waves MultiRack. Waves MultiRack will no longer run on your console. If you are running Waves MultiRack on your console, please visit <http://www.waves.com/downloads/digico> for more information.

This upgrade will involve updating all or some of the following: Console Software.

Please note that in the unlikely event that any of the serial devices fail to update correctly, you may be required to reprogram them using an ICD2 programmer. Please consult your local DiGiCo distributor for more information.

Disconnect All Optocore, MADI, Local I/O Audio and Headphone Connections before proceeding with this upgrade. Quit to Windows

The following table lists the versions and codes you will end up with after performing this update

Description	Version 1069	Version 1090
Software	10.2.1069	10.5.1090
Worksurfaces	12	12
Local I/O	55	55
Macros	9	9
PowerCon	8	8
Engine : HOST	06/09/2013	06/09/2013
Engine : FPGA	06/11/2012	06/11/2012
Engine : Effects	18/04/2012	18/04/2012
SD-Rack: Rack8b.bin	21/09/2016	21/09/2016
SD-Rack : Rack8b.bit	05/07/2012	05/07/2012
D-Rack : Drack8b.bin	10/12/2014	10/12/2014
D-Rack : Drack8b.bit	13/03/2014	13/03/2014
D2-Rack: D2rack.bin	03/11/2017	03/11/2017
D2-Rack:D2rack.bit	01/04/2014	01/04/2014
DiGiRack/MADIRack: Rack.bin	28/09/15	28/09/15
DiGiRack/MADIRack: Rack.bit	10/03/06	10/03/06

1. Copy the Software Updater **SD5CS_V1090z_Updater.exe** onto a suitable USB Key and insert into a free USB Socket on the SD5.

2. Right-Click on the **Start Menu** and choose **Explore**.

Navigate to your USB Key, and run **SD5CS_V1090z_Updater.exe** from your USB Key. This updater will install the required updates, application software, and backup your current SD5CS application folder.

3. The **UpdateHardware** application will now automatically run.

For each device, you will see the current running version in the “running” column, with the new version in the “available” column. The available version is based on the corresponding file in D:\SD5CS directory

Once complete, close the **UpdateHardware** Program and remove your USB Key from the Console.

4. From the Start Menu, shut down the console.

5. Power the console on. It will launch straight into the SD5CS application.

You should check that all the components have updated correctly in the Diagnostics Panel.

Open this from the System Menu / Diagnostics.

The First Tab (Console) will show the version for any serial devices you have updated.

The right-hand section of this window lists the Serial devices, and in the code column, you can see the version running. These should match the new release versions listed at the start of this document. If they do not, it is likely that the upgrades have failed, and you should repeat the upgrade process (from Point 3) using **D:\SD5CS\UpdateHardware.exe**.

The second Tab (Engine) will show the Engine Codes you have updated. Confirm that the Host, Effects & FPGA Code Downloaded Dates match the date listed on the first page of this document.

**If, after following all the instructions, you cannot upgrade your SD5CS, please contact
DiGiCo Technical Support.**
